

AD-A045 752

BALLISTIC RESEARCH LABS ABERDEEN PROVING GROUND MD  
A NOTE ON THE SOLUTION FOR A CIRCULAR GAS JET.(U)  
SEP 77 W WALTERS

F/G 20/4

UNCLASSIFIED

BRL-MR-2787

NL

| OF |  
ADA045752



END  
DATE  
FILMED  
11-77  
DDC

BRL MR 2787

# BRL

12

AD

AD A 045752

MEMORANDUM REPORT NO. 2787

A NOTE ON THE SOLUTION FOR A CIRCULAR  
GAS JET

William Walters

September 1977



Approved for public release; distribution unlimited.

USA ARMAMENT RESEARCH AND DEVELOPMENT COMMAND  
USA BALLISTIC RESEARCH LABORATORY  
ABERDEEN PROVING GROUND, MARYLAND

AD NO.

DDC FILE COPY

Destroy this report when it is no longer needed.  
Do not return it to the originator.

Secondary distribution of this report by originating  
or sponsoring activity is prohibited.

Additional copies of this report may be obtained  
from the National Technical Information Service,  
U.S. Department of Commerce, Springfield, Virginia  
22151.

The findings in this report are not to be construed as  
an official Department of the Army position, unless  
so designated by other authorized documents.

*The use of trade names or manufacturers' names in this report  
does not constitute indorsement of any commercial product.*

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER BRL Memorandum Report No. 2787	2. GOVT ACCESSION NO. (14)	3. RECIPIENT'S CATALOG NUMBER BRL-MR-2787
4. TITLE (and Subtitle) (6) A NOTE ON THE SOLUTION FOR A CIRCULAR GAS JET.	5. TYPE OF REPORT & PERIOD COVERED (9) Final rept.	
7. AUTHOR(s) (10) William Walters	6. PERFORMING ORG. REPORT NUMBER	
9. PERFORMING ORGANIZATION NAME AND ADDRESS USA Ballistic Research Laboratory Aberdeen Proving Ground, Maryland 21005	8. CONTRACT OR GRANT NUMBER(s)	
11. CONTROLLING OFFICE NAME AND ADDRESS U.S. Army Materiel Development & Readiness Command 5001 Eisenhower Avenue Alexandria, Virginia 22333	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS (16) RDT&E 1L161102AH43	
14. MONITORING AGENCY NAME & ADDRESS (If different from Controlling Office) (12) 11 p.	12. REPORT DATE (11) SEP 1977	
	13. NUMBER OF PAGES 13	
	15. SECURITY CLASS. (of this report) UNCLASSIFIED	
	15a. DECLASSIFICATION/DOWNGRADING SCHEDULE	
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number)		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) (mba) The classical solution for a circular gas jet given by Schlichting is obtained in exact form. An exact form of the solution is also presented for a more general form of the governing equations with boundary conditions such that the constants of integration need not be equal to zero.		

DD FORM 1 JAN 73 1473

EDITION OF 1 NOV 65 IS OBSOLETE

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

050 750

mt



# TABLE OF CONTENTS

	Page
I. INTRODUCTION . . . . .	5
II. EXACT SOLUTION OF THE CIRCULAR GAS JET EQUATION . . . . .	5
III. EXACT SOLUTION OF THE GENERAL EQUATION . . . . .	7
IV. SOLUTION FOR F . . . . .	9
DISTRIBUTION LIST . . . . .	13

ACCESSION for	
NTIS	White Section <input checked="" type="checkbox"/>
DDC	Buff Section <input type="checkbox"/>
UNANNOUNCED	<input type="checkbox"/>
JUSTIFICATION	
BY	
DISTRIBUTION/AVAILABILITY CODES	
DI	SPECIAL
A	

## I. INTRODUCTION

Schlichting<sup>1</sup> presented a solution for a laminar (or turbulent) gas jet exiting from a small circular orifice and mixing with the surrounding fluid. The pressure along and across the jet is assumed constant. The flow is axisymmetric and steady. Boundary layer theory is applicable to this problem and the velocity profiles are considered to be similar.

Under the similarity transform, the governing equation is<sup>1</sup>

$$\frac{FF'}{\eta^2} - \frac{F'^2}{\eta} - \frac{FF''}{\eta} = \frac{d}{d\eta} \left( F'' - \frac{F'}{\eta} \right) \quad (1)$$

where  $F = \frac{\psi}{\nu x}$ ,

$$\eta = \frac{y}{x},$$

prime (') denotes differentiation with respect to  $\eta$ ,

$\psi$  is the stream function,

$\nu$  is the kinematic viscosity,

$x$  is the axial coordinate, and

$y$  is the radial coordinate.

Equation (1) is a third order, ordinary, nonlinear differential equation. The boundary conditions are<sup>1</sup> at  $\eta = 0$ ,  $F = 0$  and  $F' = 0$ .

An exact form of Schlichting's solution is obtained for the given boundary conditions and an exact solution is obtained for a more general class of problems where the boundary conditions are not restricted to those specified for a freely expanding jet.

## II. EXACT SOLUTION OF THE CIRCULAR GAS JET EQUATION

Equation (1) is integrable since

$$- \frac{d}{d\eta} \left( \frac{FF'}{\eta} \right) = - \frac{FF''}{\eta} - \frac{F'^2}{\eta} + \frac{FF'}{\eta^2},$$

and direct integration of Equation (1) yields

<sup>1</sup>H. Schlichting, *Boundary Layer Theory*, McGraw-Hill Book Co., 6th ed., N.Y., 1968, p. 219-221.

$$-\frac{FF'}{\eta} = F'' - \frac{F'}{\eta} + C_1, \quad (2)$$

or  $FF' = F' - \eta F'', \quad (3)$

for the given boundary conditions. Equation (3) is a second order, nonlinear, ordinary differential equation.

Now, Equation (3) may be integrated since

$$\frac{d}{d\eta} (\eta F') - 2F' = \eta F'' - F',$$

and

$$\frac{1}{2} \frac{dF^2}{d\eta} = FF',$$

or Equation (3) becomes

$$2\eta F' = 2C_2 + 4F - F^2. \quad (4)$$

It is noteworthy that a solution to Equation (3) is given by Kamke<sup>2</sup> by transforming the independent variable. Since direct integration is possible, such transformations are unnecessary.

It is possible to separate the variables in Equation (4) or  $\frac{2dF}{2C_2 + 4F - F^2} = \frac{d\eta}{\eta}$  and integration yields,

$$-\frac{1}{x} \tanh^{-1} \frac{2-F}{2x} = \ln \eta + C_3,$$

where

$$x = \pm \frac{\sqrt{2C_2 + 4}}{2}.$$

Then the function F becomes

$$\begin{aligned} \frac{2-F}{2x} &= \tanh \left[ \ln (\eta C_3)^{-x} \right] \\ &= \frac{(\eta C_3)^{-x} - (\eta C_3)^x}{(\eta C_3)^{-x} + (\eta C_3)^x}, \end{aligned}$$

<sup>2</sup>E. Kamke, *Differentialgleichungen Lösungsmethoden und Lösungen*, Chelsea Publishing Co., 1948, p. 563.

or

$$F = \frac{2x (\eta C_3)^{2x} - 2x + 2 (\eta C_3)^{2x} + 2}{1 + (\eta C_3)^{2x}},$$

is an exact solution of Equation (3).

For the freely expanding jet, at  $\eta = 0$ ;  $F = 0$  and  $F' = 0$  or from Equation (4),  $C_2 = 0$  or  $x = \pm 1$ . \* Then,

$$F = \frac{4 (\eta C_3)^2}{1 + (\eta C_3)^2}$$

represents an exact solution to Equation (3), where  $C_3$  is an arbitrary constant. This solution satisfies the boundary condition that  $F = 0$  and  $F' = 0$  at  $\eta = 0$ , for any  $C_3$ . Note that for  $C_3 = \frac{\gamma}{2}$ , where  $\gamma$  is a constant, and for  $\xi = \gamma\eta$ ,  $F$  transforms to Schlichting's<sup>1</sup> solution or

$$F = \frac{\xi^2}{1 + \frac{1}{4} \xi^2}.$$

However, any multiple of  $C_3$  will yield a similar expression for  $F$  which satisfies the posed boundary condition. The general solution is given by

$$F = \frac{4 (\eta C_3)^2}{1 + (\eta C_3)^2},$$

and the second constant of integration,  $C_3$ , may be determined directly, from the given value of the momentum in this case.

### III. EXACT SOLUTION OF THE GENERAL EQUATION

The general expression, Equation (2) may also be solved exactly when it is not required that  $C_1$  be zero. Equation (2) can be written as

$$FF' + \eta F'' - F' - \eta C_1 = 0,$$

and integrated to yield

$$F^2 + 2\eta F' - 4F = \eta^2 C_1 + 2C_2. \quad (5)$$

\*  $x = +1$  and  $x = -1$  yield solutions of exactly the same form.



Now  $F^2 - 4F \equiv (F-2)^2 - 4$ , and Equation (5) becomes

$$(F-2)^2 + 2\eta F' = \eta^2 C_1 + 2C_2 + 4. \quad (6)$$

The left hand side (LHS) of Equation (6) is simplified by letting  $\alpha(\eta) = F(\eta) - 2$ , and Equation (6) becomes

$$\alpha^2 + 2\eta\alpha' = \eta^2 C_1 + 2C_2 + 4. \quad (7)$$

The term  $\eta$  is removed from the LHS of (7) by transforming the independent variable  $\eta$  such that  $\alpha(\eta) = \bar{\alpha}(\xi)$  and  $\xi = \ln |\eta|$ , or

$$\frac{\bar{\alpha}^2}{\alpha^2} + 2\bar{\alpha}'(\xi) = 2C_2 + 4 + C_1 e^{2\xi}. \quad (8)$$

The constant coefficients are rearranged by letting  $y(\xi) = \frac{\bar{\alpha}(\xi)}{2}$ , then Equation (8) becomes,

$$y^2 + y' = \frac{e^{2\xi} C_1}{4} + \frac{C_2}{2} + 1. \quad (9)$$

Equation (9) is of the Riccati type and may be transformed to a linear equation. This is accomplished by the Riccati transformation

$$u'(\xi) = y(\xi) u(\xi),$$

and Equation (9) becomes

$$u'' = u \left[ \frac{e^{2\xi} C_1}{4} + \frac{C_2}{2} + 1 \right]. \quad (10)$$

Now, the inverse transformation on the independent variable  $\xi$ , where

$$u(\xi) = \bar{u}(z), \quad z = \sqrt{\frac{C_1}{4}} e^\xi$$

yields,

$$z^2 \bar{u}'' + z \bar{u}' - \left( z^2 + \frac{C_2}{2} + 1 \right) \bar{u} = 0. \quad (11)$$

Equation (11) is the modified Bessel equation for  $\nu^2 = \frac{C_2}{2} + 1$ . The solutions are  $I_\nu(z)$  and  $K_\nu(z)$  which are modified Bessel functions of

the first and second kind respectively<sup>3</sup>, or

$$\bar{u} = A I_{\pm \nu}(z) + B K_{\nu}(z), \quad (12)$$

where A and B are arbitrary constants and  $I_{\nu}$  and  $I_{-\nu}$  are linearly dependent if  $\nu$  is an integer. Also  $I_{\nu}(z)$  and  $K_{\nu}(z)$  are real and positive for  $z > 0$  and  $\nu > -1$ .

Thus, Equation (2) may be solved by transforming it into a Riccati equation and then into a modified Bessel equation. Once boundary conditions are stipulated, the integration constants can be determined and the solution for  $\bar{u}$  can be transformed back to F. This is not carried out for the general case, since the order of the modified Bessel functions ( $\nu$ ) depends on the value of  $C_2$ . I.e., it is preferable to know whether  $\nu$  is an integer or non-integer before proceeding with the inverse transformations.

Solutions of this type are applicable to equations such as those for a steady state boundary layer, where similarity transforms can yield exact solutions.

#### IV. SOLUTION FOR F

Utilizing the boundary condition that when the radial coordinate is zero, the radial velocity is zero and the axial velocity represents some mean value implies<sup>1</sup>

$$\text{at } \eta = 0; F = 0 \text{ and } F' = 0,$$

or from Equation (5),  $C_2 = 0$ .

In this case  $\nu = \pm 1$ ,  $I_1(z)$  and  $I_{-1}(z)$  are linearly dependent (in fact, equal) and the general solution (12) becomes

$$\bar{u} = A I_1(z) + B K_1(z). \quad (13)$$

Then,

$$u(\xi) = A I_1\left(\sqrt{\frac{C_1}{4}} e^{\xi}\right) + B K_1\left(\sqrt{\frac{C_1}{4}} e^{\xi}\right),$$

<sup>3</sup>*Handbook of Mathematical Functions With Formulas, Graphs, and Mathematical Tables*, Edited by M. Abramowitz and I. Stegun, National Bureau of Standards, Applied Mathematics Series, 55, June, 1964, p. 374.

$$y(\xi) = \sqrt{\frac{C_1}{2}} e^{\xi} \left[ \frac{AI_1' \left( \sqrt{\frac{C_1}{2}} e^{\xi} \right) + BK_1' \left( \sqrt{\frac{C_1}{2}} e^{\xi} \right)}{AI_1 \left( \sqrt{\frac{C_1}{2}} e^{\xi} \right) + BK_1 \left( \sqrt{\frac{C_1}{2}} e^{\xi} \right)} \right],$$

$$\alpha(\eta) = \sqrt{C_1} \eta \left[ \frac{AI_1' \left( \sqrt{\frac{C_1}{2}} \eta \right) + BK_1' \left( \sqrt{\frac{C_1}{2}} \eta \right)}{AI_1 \left( \sqrt{\frac{C_1}{2}} \eta \right) + BK_1 \left( \sqrt{\frac{C_1}{2}} \eta \right)} \right]$$

and finally,

$$F = 2 + \sqrt{C_1} \eta \left[ \frac{AI_1' \left( \sqrt{\frac{C_1}{2}} \eta \right) + BK_1' \left( \sqrt{\frac{C_1}{2}} \eta \right)}{AI_1 \left( \sqrt{\frac{C_1}{2}} \eta \right) + BK_1 \left( \sqrt{\frac{C_1}{2}} \eta \right)} \right]$$

results. Note that the numerator and denominator of the expression in brackets may be divided by A or B, so A and B are not independent. One constant can always be eliminated. This results from the use of the Riccati transformation used to obtain Equation (10). This transformation converted a first order Equation, (9), into a second order Equation, (10), thereby introducing an additional constant. The two constants of integration associated with Equation (2) are  $C_1$  and A or B. The constant  $C_1$  appears in Equation (2) and  $C_2$  has already been evaluated.

Finally, the expression for F may be written as

$$F = 2 - \sqrt{C_1} + \frac{C_1 \eta}{2} \left( \frac{AI_0 \left( \sqrt{\frac{C_1}{2}} \eta \right) - BK_0 \left( \sqrt{\frac{C_1}{2}} \eta \right)}{AI_1 \left( \sqrt{\frac{C_1}{2}} \eta \right) + BK_1 \left( \sqrt{\frac{C_1}{2}} \eta \right)} \right).$$

From the expression for F, the radial and axial velocities and their derivatives may be obtained, in a manner analogous to Schlichting's treatment. For this general formulation, boundary conditions must be

specified to determine  $C_1$  and A or B.

#### ACKNOWLEDGMENTS

The author wishes to acknowledge Dr. R. Sedney for his many constructive comments and his careful review of this report. The author is also grateful to Dr. A. Dietrich and Mr. R. Jameson for their cooperation in this study.



# DISTRIBUTION LIST

<u>No. of Copies</u>	<u>Organization</u>	<u>No. of Copies</u>	<u>Organization</u>
12	Commander Defense Documentation Center ATTN: DDC-TCA Cameron Station Alexandria, VA 22314	1	Commander US Army Tank Automotive Development Command ATTN: DRDTA-RWL Warren, MI 48090
1	Commander US Army Materiel Development and Readiness Command ATTN: DRCDMA-ST 5001 Eisenhower Avenue Alexandria, VA 22333	2	Commander US Army Mobility Equipment Research & Development Cmd ATTN: Tech Docu Cen, Bldg. 315 DRSME-RZT Fort Belvoir, VA 22060
1	Commander US Army Aviation Research and Development Command ATTN: DRSAV-E 12th and Spruce Streets St. Louis, MO 63166	1	Commander US Army Armament Materiel Readiness Command Rock Island, IL 61202
1	Director US Army Air Mobility Research and Development Laboratory Ames Research Center Moffett Field, CA 94035	1	Commander US Army Harry Diamond Labs ATTN: DRXDO-TI 2800 Powder Mill Road Adelphi, MD 20783
1	Commander US Army Missile Research and Development Command ATTN: DRDMI-R Redstone Arsenal, AL 35809	1	Director US Army TRADOC Systems Analysis Activity ATTN: ATAA-SA White Sands Missile Range NM 88002
1	Commander US Army Electronics Command ATTN: DRSEL-RD Fort Monmouth, NJ 07703	1	University of Illinois Department of Aeronautical and Astronautical Engineering ATTN: Prof. S. M. Yen Urbana, IL 61801

## Aberdeen Proving Ground

Marine Corps Ln Ofc  
Dir, USAMSAA